

Electromagnetic compatibility (EMC)

Part 4-1: Testing and measurement
techniques — Overview of IEC 61000-4
series

<http://www.china-gauges.com/>

The European Standard EN 61000-4-1:2007 has the status of a
British Standard

ICS 33.100.01; 33.100.20

National foreword

This British Standard was published by BSI. It is the UK implementation of EN 61000-4-1:2007. It is identical with IEC 61000-4-1:2006. It supersedes BS EN 61000-4-1:2001, which will be withdrawn on 1 February 2010.

The UK participation in its preparation was entrusted by Technical Committee GEL/210, EMC — Policy committee, to Subcommittee GEL/210/2, EMC — Basic and generic standards.

A list of organizations represented on GEL/210/2 can be obtained on request to its secretary.

This publication does not purport to include all the necessary provisions of a contract. Users are responsible for its correct application.

Compliance with a British Standard cannot confer immunity from legal obligations.

<http://www.china-gauges.com/>

This British Standard was published under the authority of the Standards Policy and Strategy Committee on 30 March 2007

Amendments issued since publication

Amd. No.	Date	Comments

© BSI 2007

ISBN 978 0 580 50454 9

English version

**Electromagnetic compatibility (EMC) -
Part 4-1: Testing and measurement techniques -
Overview of IEC 61000-4 series**

(IEC 61000-4-1:2006)

Compatibilité électromagnétique (CEM) -
Partie 4-1: Techniques d'essai
et de mesure -
Vue d'ensemble de la série CEI 61000-4
(CEI 61000-4-1:2006)

Elektromagnetische Verträglichkeit
(EMV) -
Teil 4-1: Prüf- und Messverfahren -
Übersicht über die Reihe IEC 61000-4
(IEC 61000-4-1:2006)

This European Standard was approved by CENELEC on 2007-02-01. CENELEC members are bound to comply with the CEN/CENELEC Internal Regulations which stipulate the conditions for giving this European Standard the status of a national standard without any alteration.

Up-to-date lists and bibliographical references concerning such national standards may be obtained on application to the Central Secretariat or to any CENELEC member.

This European Standard exists in three official versions (English, French, German). A version in any other language made by translation under the responsibility of a CENELEC member into its own language and notified to the Central Secretariat has the same status as the official versions.

CENELEC members are the national electrotechnical committees of Austria, Belgium, Bulgaria, Cyprus, the Czech Republic, Denmark, Estonia, Finland, France, Germany, Greece, Hungary, Iceland, Ireland, Italy, Latvia, Lithuania, Luxembourg, Malta, the Netherlands, Norway, Poland, Portugal, Romania, Slovakia, Slovenia, Spain, Sweden, Switzerland and the United Kingdom.

CENELEC

European Committee for Electrotechnical Standardization
Comité Européen de Normalisation Electrotechnique
Europäisches Komitee für Elektrotechnische Normung

Central Secretariat: rue de Stassart 35, B - 1050 Brussels

Foreword

The text of document 77/319/FDIS, future edition 3 of IEC 61000-4-1, prepared by IEC TC 77, Electromagnetic compatibility, was submitted to the IEC-CENELEC parallel vote and was approved by CENELEC as EN 61000-4-1 on 2007-02-01.

This European Standard supersedes EN 61000-4-1:2000.

Changes introduced in EN 61000-4-1:2007 are for the purpose of updating the text to include reference to the latest publications of the EN 61000-4 series.

The following dates were fixed:

- latest date by which the EN has to be implemented at national level by publication of an identical national standard or by endorsement (dop) 2007-11-01
- latest date by which the national standards conflicting with the EN have to be withdrawn (dow) 2010-02-01

Annex ZA has been added by CENELEC.

Endorsement notice

The text of the International Standard IEC 61000-4-1:2006 was approved by CENELEC as a European Standard without any modification.

CONTENTS

INTRODUCTION 4

1 Scope and object..... 5

2 Normative references 5

3 Terms and definitions 7

4 General 8

5 Structure of the IEC 61000-4 series standards 8

6 Selection of tests 8

7 Test report 12

Annex ZA (normative) Normative references to international publications with their
corresponding European publications 16

Table 1 – Applicability of immunity tests based on location (environment)..... 13

Table 2 – Applicability of immunity tests based on EUT ports 15

<http://www.china-gauges.com/>

INTRODUCTION

The IEC 61000 series is published in several parts according to the following structure:

Part 1: General

General consideration (introduction, fundamental principles)
Definitions, terminology

Part 2: Environment

Description of the environment
Classification of the environment
Compatibility levels

Part 3: Limits

Emission limits
Immunity test levels (in so far as they do not fall under the responsibility of the product committees)

Part 4: Testing and measurement techniques

Measurement techniques
Testing techniques

Part 5: Installation and mitigation guidelines

Installation guidelines
Mitigation methods and devices

Part 6: Generic standards

Part 9: Miscellaneous

Each part is further subdivided into several parts, published either as International Standards, technical specifications or technical reports, some of which have already been published as sections. Others will be published with the part number followed by a dash and completed by a second number identifying the subdivision (example: 61000-6-1).

<http://www.china-gauges.com/>

ELECTROMAGNETIC COMPATIBILITY (EMC) –

Part 4-1: Testing and measurement techniques – Overview of IEC 61000-4 series

1 Scope and object

This part of IEC 61000 covers testing and measuring techniques for electric and electronic equipment (apparatus and systems) in its electromagnetic environment.

The object of this part is to give applicability assistance to the technical committees of IEC or other bodies, users and manufacturers of electrical and electronic equipment on EMC standards within the IEC 61000-4 series on testing and measurement techniques and to provide general recommendations concerning the choice of relevant tests.

2 Normative references

The following referenced documents are indispensable for the application of this document. For dated references, only the edition cited applies. For undated references, the latest edition of the referenced document (including any amendments) applies.

IEC 60050(161), *International Electrotechnical Vocabulary (IEV) – Chapter 161: Electromagnetic compatibility*

IEC 61000-1-1, *Electromagnetic Compatibility (EMC) – Part 1-1: General – Application and interpretation of fundamental definitions and terms*

IEC 61000-2-5, *Electromagnetic Compatibility (EMC) – Part 2: Environment – Classification of electromagnetic environments*

IEC 61000-3-2, *Electromagnetic compatibility (EMC) – Part 3-2: Limits – Limits for harmonic current emissions (equipment input current ≤ 16 A per phase)*

IEC 61000-3-3, *Electromagnetic compatibility (EMC) – Part 3-3: Limits – Limitation of voltage changes, voltage fluctuations and flicker in public low-voltage supply systems, for equipment with rated current ≤ 16 A per phase and not subject to conditional connection*

IEC/TS 61000-3-4, *Electromagnetic compatibility (EMC) – Part 3-4: Limits – Limitation of emission of harmonic currents in low-voltage power supply systems for equipment with rated current greater than 16 A*

IEC/TR 61000-3-5, *Electromagnetic compatibility (EMC) – Part 3-5: Limits – Limitation of voltage fluctuations and flicker in low-voltage power supply systems for equipment with rated current greater than 16 A*

IEC 61000-3-6, *Electromagnetic compatibility (EMC) – Part 3: Limits – Section 6: Assessment of emission limits for distorting loads in MV and HV power systems*

IEC 61000-3-11, *Electromagnetic compatibility (EMC) – Part 3-11: Limits – Limitation of voltage changes, voltage fluctuations and flicker in public low-voltage supply systems – Equipment with rated current ≤ 75 A and subject to conditional connection*

IEC 61000-3-12, *Electromagnetic compatibility (EMC) – Part 3-12: Limits – Limits for harmonic currents produced by equipment connected to public low-voltage systems with input current > 16 A and ≤ 75 A per phase*

IEC 61000-4-2, *Electromagnetic compatibility (EMC) – Part 4-2: Testing and measurement techniques – Electrostatic discharge immunity test*

IEC 61000-4-3, *Electromagnetic compatibility (EMC) – Part 4-3: Testing and measurement techniques – Radiated, radio-frequency, electromagnetic field immunity test*

IEC 61000-4-4, *Electromagnetic compatibility (EMC) – Part 4-4: Testing and measurement techniques – Electrical fast transient/burst immunity test*

IEC 61000-4-5, *Electromagnetic compatibility (EMC) – Part 4-5: Testing and measurement techniques – Surge immunity test*

IEC 61000-4-6, *Electromagnetic compatibility (EMC) – Part 4-6: Testing and measurement techniques – Immunity to conducted disturbances, induced by radio-frequency fields*

IEC 61000-4-7, *Electromagnetic compatibility (EMC) – Part 4-7: Testing and measurement techniques – General guide on harmonics and interharmonics measurements and instrumentation, for power supply systems and equipment connected thereto*

IEC 61000-4-8, *Electromagnetic compatibility (EMC) – Part 4-8: Testing and measurement techniques – Power frequency magnetic field immunity test*

IEC 61000-4-9, *Electromagnetic compatibility (EMC) – Part 4-9: Testing and measurement techniques – Pulse magnetic field immunity test*

IEC 61000-4-10, *Electromagnetic compatibility (EMC) – Part 4-10: Testing and measurement techniques – Damped oscillatory magnetic field immunity test*

IEC 61000-4-11, *Electromagnetic compatibility (EMC) – Part 4-11: Testing and measurement techniques – Voltage dips, short interruptions and voltage variations immunity test*

IEC 61000-4-12, *Electromagnetic compatibility (EMC) – Part 4-12: Testing and measurement techniques – Oscillatory waves immunity test*

IEC 61000-4-13, *Electromagnetic compatibility (EMC) – Part 4-13: Testing and measurement techniques – Harmonics and interharmonics including mains signalling at a.c. power port, low frequency immunity tests*

IEC 61000-4-14, *Electromagnetic compatibility (EMC) – Part 4-14: Testing and measurement techniques – Voltage fluctuation immunity test*

IEC 61000-4-15, *Electromagnetic compatibility (EMC) – Part 4-15: Testing and measurement techniques – Flickermeter – Functional and design specifications*¹

IEC 61000-4-16, *Electromagnetic compatibility (EMC) – Part 4-16: Testing and measurement techniques – Test for immunity to conducted common mode disturbances in the frequency range 0 Hz to 150 kHz immunity test*

¹ Revision of IEC 60868.

IEC 61000-4-17, *Electromagnetic compatibility (EMC) – Part 4-17: Testing and measurement techniques – Ripple on d.c. input power port immunity test*

IEC 61000-4-18, *Electromagnetic Compatibility (EMC) – Part 4-18: Testing and measurement techniques – Oscillatory wave immunity test*

IEC 61000-4-20, *Electromagnetic compatibility (EMC) – Part 4-20: Testing and measurement techniques – Emission and immunity testing in transverse electromagnetic (TEM) waveguides*

IEC 61000-4-21, *Electromagnetic compatibility (EMC) – Part 4-21: Testing and measurement techniques – Reverberation chamber test methods*

IEC 61000-4-23, *Electromagnetic compatibility (EMC) – Part 4-23: Testing and measurement techniques – Test methods for protective devices for HEMP and other radiated disturbances*

IEC 61000-4-24, *Electromagnetic compatibility (EMC) – Part 4: Testing and measurement techniques – Section 24: Test methods for protective devices for HEMP conducted disturbance*

IEC 61000-4-25, *Electromagnetic compatibility (EMC) – Part 4-25: Testing and measurement techniques – HEMP immunity test methods for equipment and systems*

IEC 61000-4-27, *Electromagnetic compatibility (EMC) – Part 4-27 : Testing and measurement techniques – Unbalance, immunity test*

IEC 61000-4-28, *Electromagnetic compatibility (EMC) – Part 4-28: Testing and measurement techniques – Variation of power frequency, immunity test*

IEC 61000-4-29, *Electromagnetic compatibility (EMC) – Part 4-29: Testing and measurement techniques – Voltage dips, short interruptions and voltage variations on d.c. input power port immunity tests*

IEC 61000-4-30, *Electromagnetic compatibility (EMC) – Part 4-30: Testing and measurement techniques – Power quality measurement methods*

IEC 61000-4-32, *Electromagnetic compatibility (EMC) – Part 4-32: Testing and measurement techniques – High-altitude electromagnetic pulse (HEMP) simulator compendium*

IEC 61000-4-33, *Electromagnetic compatibility (EMC) – Part 4-33: Testing and measurement techniques – Measurement methods for high power transient parameters*

IEC 61000-4-34, *Electromagnetic compatibility (EMC) – Part 4-34: Testing and measurement techniques – Voltage dips, short interruptions and voltage variations immunity tests for equipment with input current more than 16 A per phase*

3 Terms and definitions

For the purposes of this document, the definitions in IEC 60050(161) apply.

4 General

In the past, electromechanical devices and systems were generally not sensitive to electromagnetic disturbances (i.e. conducted and radiated electromagnetic disturbances and electrostatic discharge). The electronic components and equipment now in use are much more sensitive to these disturbances, particularly to "high-frequency" and "transient" phenomena. The tremendous expansion in the use of electronic components and equipment has increased the danger and importance of malfunctioning, damage, etc. which can arise from electric and electromagnetic disturbances.

The product committees (or users and manufacturers of equipment) remain responsible for the appropriate choice of the immunity tests from the IEC 61000-4 series and the test level to be applied to their equipment. However, to enhance the task of coordination and standardization, the product committees or users and manufacturers should consider the recommendations given in this standard.

5 Structure of the IEC 61000-4 series standards

The structure of standards within the IEC 61000-4 series in general follows the guidance given in IEC Guide 107. For the basic testing standards of the series, that structure is as follows:

1. Scope
2. Normative references
3. Terms and definitions
4. General
5. Test levels/limits
6. Test equipment
7. Test set-up
8. Test procedures
9. Evaluation of test results
10. Test report

There are standards within the IEC 61000-4 series, which are not basic testing standards (for example IEC 61000-4-7). They are standards related to measurement (instrumentation and procedures), which do not necessarily follow the above-mentioned structure.

6 Selection of tests

Tests can be applied to equipment for many reasons, for example

- design tests during development;
- type tests;
- acceptance tests;
- production tests.

Equipment should be subjected to all tests necessary to provide the required reliability, but, for economic reasons, the number of tests may be limited to a reasonable minimum. It is acceptable that the number of tests for acceptance or production testing is reduced in comparison with type tests.

The selection of the tests to be applied to a particular equipment depends on several factors, such as

- types of disturbances affecting the equipment;
- environmental conditions;
- required reliability and behaviour;
- economic constraints;
- equipment characteristics.

With regard to the variety of equipment and environmental conditions to be considered, it is difficult to indicate exact rules concerning the selection of tests. This selection is primarily the responsibility of the product committee concerned (based on their experience). In special cases, this can be fixed by agreement between the manufacturer and the user. In all cases, knowledge of the electromagnetic environment (the IEC 61000-2 series, especially IEC 61000-2-5) and awareness of the statistical aspects explained in IEC 61000-1-1 will be helpful.

If there is an existing applicable generic standard, product family standard or a dedicated product standard, these standards have the following priority (see IEC Guide 107):

- dedicated product standard;
- product family standard;
- generic standard.

If it is considered that these standards are not applicable to a particular type of equipment, the following short explanation of each part of the IEC 61000-4 series may be helpful. A summary is also given in Tables 1 and 2.

- **Test according to IEC 61000-4-2 (*Electrostatic discharge immunity test*)**

In general, the electrostatic discharge test is applicable to all equipment which is used in an environment where electrostatic discharges may occur. Direct and indirect discharges shall be considered. Exclusions may include equipment limited for use in ESD-controlled environmental conditions and non-electrical or electronic products.

- **Test according to IEC 61000-4-3 (*Radiated, radio-frequency, electromagnetic field immunity test*)**

In general, the radiated immunity test is applicable to all products, where radio-frequency fields are present. Exclusions may include equipment limited for use in electromagnetic-controlled conditions or low electromagnetic field environment and non-electrical or electronic products..

- **Test according to IEC 61000-4-4 (*Electrical fast transient/burst immunity test*)**

In general, the fast transient test is applicable to products which are connected to mains or have cables (signal or control) in close proximity to mains.

- **Test according to IEC 61000-4-5 (*Surge immunity test*)**

The surge test is applicable to products which are connected to networks leaving the building or mains in general.

- **Test according to IEC 61000-4-6** (*Immunity test to conducted disturbances induced by radio-frequency fields*)

In general, the conducted immunity test is applicable to products, where radio-frequency fields are present and which are connected to mains or other networks (signal or control lines).

- **IEC 61000-4-7** (*General guide on harmonics and interharmonics measurements and instrumentation, for power supply systems and equipment connected thereto*)

This technical report defines the measurement method of harmonics and interharmonics. It compares the characteristics of an analogue measuring equipment and of a digital measuring equipment. It provides also the accuracy awaited and the test set-up. It is applicable to voltage or current measurements in the d.c. frequency range up to 2 500 Hz, especially with regard to the emission requirements according to IEC 61000-3-2, IEC 61000-3-4, IEC 61000-3-6, IEC 61000-3-12 and IEC 61000-4-30.

- **Test according to IEC 61000-4-8** (*Power frequency magnetic field immunity test*)

In general, this test should be limited to products which are susceptible to magnetic fields (for example Hall effect devices, CRT and special products to be installed in high magnetic field environments). Exclusions include equipment which is intended for use in a low magnetic field environment.

- **Test according to IEC 61000-4-9** (*Pulse magnetic field immunity test*)

This test is mainly applicable to products to be installed in electrical plants (for example telecontrol centres in close proximity to switchgear).

- **Test according to IEC 61000-4-10** (*Damped oscillatory magnetic field immunity test*)

This test is mainly applicable to products to be installed in high-voltage substations.

- **Test according to IEC 61000-4-11** (*Voltage dips, short interruptions and voltage variations immunity test*)

This document defines the test methods to evaluate the immunity of an equipment connected to the LV system, to voltage dips, short interruptions and voltage variations. This test is applicable to equipment with a rated input current of less than 16 A per phase, connected to a.c. mains. The standard describes also different levels of tests, four performance criteria, the operating condition when the equipment is tested and the test set-up. It is a basic standard which can be used as a tool for the product committees which are defining their own EMC immunity standard.

- **Test according to IEC 61000-4-12** (*Oscillatory wave immunity test*)

The ring wave test is applicable to equipment connected to a.c. mains in certain countries (for example the mains network in the USA). The damped oscillatory wave test is applicable to equipment used in power plants and high-voltage substations (for example static relays).

- **Test according to IEC 61000-4-13** (*Harmonics, interharmonics including mains signalling at a.c. power port, low-frequency immunity tests*)

This test may be applied to equipment sensitive to precise zero crossing in time on the a.c. mains or to specific harmonic components.

- **Test according to IEC 61000-4-14** (*Voltage fluctuation immunity test*)

In general, voltage fluctuations have an amplitude not exceeding 10 %; therefore, most equipment is not disturbed by voltage fluctuations. However, this test may be applicable to equipment intended to be installed at locations where the mains have larger fluctuations.

- **Test according to IEC 61000-4-15** (*Flickermeter – Functional and design specifications*)

This is a specification for a flickermeter, intended to indicate correct flicker perception level for all practical voltage fluctuation waveforms, especially with regard to the emission requirements according to IEC 61000-3-3, IEC 61000-3-5 and IEC 61000-3-11.

- **Test according to IEC 61000-4-16** (*Test for immunity to conducted, common mode disturbances in the frequency range 0 Hz to 150 kHz*)

This test shall only be used for very special equipment in large installations (for example industrial plants). This document defines the *test method* to evaluate the immunity of an equipment to *conducted common mode disturbances* in the frequency range 0 Hz to 150 kHz. The standard describes also different levels of tests, four performance criteria, the operating condition when the equipment is tested and the test set-up. It is a basic standard which can be used as a tool for the product committees which are defining their own EMC immunity standard.

- **Test according to IEC 61000-4-17** (*Ripple on d.c. input power port immunity test*)

This test applies to equipment connected to d.c. distribution systems with external batteries charged during the operation of the equipment.

- **Test according to IEC 61000-4-20** (*Emission and immunity testing in transverse electromagnetic (TEM) waveguides*)

This standard specifies equipment and test procedures for testing to radiated electromagnetic fields in TEM cells.

- **Test according to IEC 61000-4-21** (*Reverberation chambers*)

This standard specifies equipment and test procedures for testing to radiated electromagnetic fields in reverberation chambers.

- **Test according to IEC 61000-4-23** (*Test methods for protective devices for HEMP and other radiated disturbance*)

This standard covers testing of protective elements designed to reduce the level of radiated electromagnetic fields from HEMP and other high power transients.

- **Test according to IEC 61000-4-24** (*Test methods for protective devices for HEMP conducted disturbance*)

This standard covers testing of voltage breakdown and voltage-limiting characteristics of HEMP protective devices

- **Test according to IEC 61000-4-25** (*HEMP immunity test and test methods for equipment and systems*)

This standard specifies the basic HEMP test methods and levels appropriate for radiated and conducted immunity testing. It is applicable for equipment and systems intended to survive a HEMP.

- **Test according to IEC 61000-4-27** (*Unbalance immunity test*)

This test may be applicable to three-phase equipment with a rated input current up to 16 A per phase, connected to a three-phase a.c. mains. However, this test is not applicable to equipment taking three-phase power but using it in a single-phase manner.

- **Test according to IEC 61000-4-28** (*Variation of power frequency, immunity test*)
In general, the test for variation of the power frequency is not applicable. However, it may apply to equipment intended to be installed at locations where the power frequency has large variations (for example equipment connected to an emergency power supply).
- **Test according to IEC 61000-4-29** (*Voltage dips, interruptions and voltage variations on d.c. input power ports, immunity tests*)
In general, this test is applicable for d.c. input power ports.
- **Test according to IEC 61000-4-30** (*Measurements of power quality parameters*)
This standard gives clarification on the measurement of power quality parameters.
- **Test according to IEC 61000-4-32** (*HEMP simulator compendium*)
This technical report provides information on the world wide availability and applicability of large scale HEMP simulators.
- **Test according to IEC 61000-4-33** (*Measurement methods for high power transient parameters*)
This standard provides a basic description of the methods and means of measuring responses from high power transient electromagnetic radiated and conducted disturbances
- **Test according to IEC 61000-4-34** (*Voltage dips short interruptions and voltage variations immunity tests for equipment with input current more than 16 A per phase*)
This test is applicable to equipment with a rated input current greater than 16 A per phase, connected to a.c. mains.

A guide to the applicability of the various standards is given in Table 1.

When any of the standards listed in Table 1 is applied, the corresponding entry in Table 2 gives a guide to the selection of the EUT ports to be tested.

7 Test report

The test report shall contain all the information necessary to reproduce the test. In particular, the following shall be recorded:

- identification of the EUT and any associated equipment, for example, brand name, product type, serial number;
- identification of the test equipment, for example, brand name, product type, serial number;
- any special environmental conditions in which the test was performed, for example, shielded enclosure;
- any specific conditions necessary to enable the test to be performed;
- performance level defined by the manufacturer, requestor or purchaser;
- performance criterion specified in the generic, product or product-family standard;
- any effects on the EUT observed during or after the application of the test disturbance, and the duration for which these effects persist;

- the rationale for the pass/fail decision (based on the performance criterion specified in the generic, product or product-family standard, or agreed between the manufacturer and the purchaser);
- any specific conditions of use, for example cable length or type, shielding or grounding or EUT operating conditions, which are required to achieve compliance.

Table 1 – Applicability of immunity tests based on location (environment)

Basic standard	Description	Applicability ^a		
		Residential, commercial and light industrial	Industrial area	Special (e.g. power plant)
61000-4-2	ESD	g.a.	g.a.	g.a.
61000-4-3	Radiated electromagnetic field	g.a.	g.a.	g.a.
61000-4-4	EFT/Burst	g.a.	g.a.	g.a.
61000-4-5	Surge	g.a.	g.a.	g.a.
61000-4-6	Conducted disturbances by RF fields	g.a.	g.a.	g.a.
61000-4-7	General guide on harmonics and interharmonics measurements and instrumentation	n.i.s.	n.i.s.	n.i.s.
61000-4-8	50/60 Hz magnetic field	may	may	g.a.
61000-4-9	Pulse magnetic field	g.n.a.	g.n.a.	g.a.
61000-4-10	Damped oscillatory magnetic field	g.n.a.	g.n.a.	g.a.
61000-4-11	Voltage dips and short interruptions	g.a.	g.a.	g.a.
61000-4-12	Oscillatory waves "ring wave"	may	may	may
61000-4-13	Harmonics, interharmonics, main signalling	may	may	may
61000-4-14	Voltage fluctuations	may	may	may
61000-4-15	Flickermeter	n.i.s.	n.i.s.	n.i.s.
61000-4-16	Conducted common mode disturbances in the range of 0 Hz to 150 kHz	g.n.a.	may	g.n.a.
61000-4-17	Ripple on DC power supply	g.n.a.	may	g.n.a.
61000-4-18	Oscillatory waves immunity test	g.n.a.	may	may
61000-4-19	Free			
61000-4-20	TEM waveguides	b	b	b
61000-4-21	Reverberation chambers	b	b	b
61000-4-22	Free			
61000-4-23	Test methods for protective device; HEMP radiated disturbance	g.n.a.	g.n.a.	g.n.a.
61000-4-24	Test methods for protective device; HEMP conducted disturbance	g.n.a.	g.n.a.	g.n.a.
61000-4-25	Test methods for equipment and systems; HEMP	g.n.a.	g.n.a.	g.n.a.
61000-4-27	Unbalance in three-phase mains	may	may	may
61000-4-28	Variation of power frequency	g.n.a.	g.n.a.	g.n.a.

Table 1 (continued)

Basic standard	Description	Applicability ^a		
		Residential, commercial and light industrial	Industrial area	Special (e.g. power plant)
61000-4-29	Voltage dips, interruptions and voltage variations on DC power ports	may	may	may
61000-4-30	Measurement of power quality parameters	n.i.s.	n.i.s.	n.i.s.
61000-4-32	HEMP simulator compendium	n.i.s.	n.i.s.	n.i.s.
61000-4-33	Measurement methods for high power transient parameters	n.i.s.	n.i.s.	n.i.s.
61000-4-34	Voltage dips and interruption	g.a.	g.a.	g.a.
<p>^a Applicability explanation: n.i.s. = not an immunity standard g.a. = generally applicable except in special cases g.n.a. = generally not applicable except in special cases may = may be applicable in certain circumstances.</p> <p>^b Test method which is subject to restrictions given in the basic standard.</p>				

Table 2 – Applicability of immunity tests based on EUT ports

Basic standard	Description	Applicability ^a				
		AC power	DC power	En-closure	Signal data	Earth
61000-4-2	ESD	—	g.n.a.	g.a.	g.a.	g.n.a.
61000-4-3	Radiated electromagnetic field	g.n.a.	g.n.a.	g.a.	g.n.a.	g.n.a.
61000-4-4	EFT/Burst	g.a.	g.a.	—	g.a.	g.a.
61000-4-5	Surge	g.a.	may	—	may	may
61000-4-6	Conducted disturbances by RF fields	g.a.	g.a.	—	g.a.	g.a.
61000-4-7	General guide on harmonics and interharmonics measurements and instrumentation	n.i.s.	n.i.s.	n.i.s.	n.i.s.	n.i.s.
61000-4-8	50/60 Hz magnetic field	—	—	may	—	—
61000-4-9	Pulse magnetic field	—	—	may	—	—
61000-4-10	Oscillatory magnetic field	—	—	may	—	—
61000-4-11	Voltage dips and interruption	g.a.	—	—	—	—
61000-4-12	Oscillatory waves "ring wave"	may	g.n.a.	—	may	g.n.a.
61000-4-13	Harmonics, interharmonics, mains signalling	may	—	—	may	—
61000-4-14	Voltage fluctuations	g.n.a.	—	—	—	—
61000-4-15	Flickermeter	n.i.s.	n.i.s.	n.i.s.	n.i.s.	n.i.s.
61000-4-16	Conducted disturbances in the range 0 Hz to 150 kHz	g.n.a.	g.n.a.	—	g.n.a.	—
61000-4-17	Ripple on DC power supply	—	may	—	—	—
61000-4-18	Oscillatory waves immunity test	may	may	—	may	may
61000-4-19	Free					
61000-4-20	TEM waveguides	—	—	—	—	—
61000-4-21	Reverberation chambers	—	—	—	—	—
61000-4-22	Free					
61000-4-23	Test methods for protective device; HEMP radiated disturbance	g.n.a.	g.n.a.	g.n.a.	g.n.a.	g.n.a.
61000-4-24	Test methods for protective device; HEMP conducted disturbance	g.n.a.	g.n.a.	g.n.a.	g.n.a.	g.n.a.
61000-4-25	Test methods for equipment and systems; HEMP	g.n.a.	g.n.a.	g.n.a.	g.n.a.	g.n.a.
61000-4-27	Unbalance in three-phase mains	may	—	—	—	—
61000-4-28	Variation of power frequency	g.n.a.	—	—	—	—
61000-4-29	Voltage dips, interruptions and voltage variations on DC power ports	—	may	—	—	—
61000-4-30	Measurement of power quality parameters	n.i.s.	n.i.s.	n.i.s.	n.i.s.	n.i.s.
61000-4-32	HEMP simulator compendium	n.i.s.	n.i.s.	n.i.s.	n.i.s.	n.i.s.
61000-4-33	Measurement methods for high power transient parameters	n.i.s.	n.i.s.	n.i.s.	n.i.s.	n.i.s.
61000-4-34	Voltage dips and interruption	g.a.	—	—	—	—

^a Applicability explanation:
n.i.s. = not an immunity standard
g.a. = generally applicable except in special cases
g.n.a. = generally not applicable except in special cases
may = may be applicable in certain circumstances.
(—) means not applicable.

Annex ZA (normative)

Normative references to international publications with their corresponding European publications

The following referenced documents are indispensable for the application of this document. For dated references, only the edition cited applies. For undated references, the latest edition of the referenced document (including any amendments) applies.

NOTE When an international publication has been modified by common modifications, indicated by (mod), the relevant EN/HD applies.

<u>Publication</u>	<u>Year</u>	<u>Title</u>	<u>EN/HD</u>	<u>Year</u>
IEC 60050-161	- ¹⁾	International Electrotechnical Vocabulary (IEV) Chapter 161: Electromagnetic compatibility	-	-
IEC/TR 61000-1-1	- ¹⁾	Electromagnetic compatibility (EMC) - Part 1: General - Section 1: Application and interpretation of fundamental definitions and terms	-	-
IEC 61000-2-5	- ¹⁾	Electromagnetic compatibility (EMC) - Part 2: Environment - Section 5: Classification of electromagnetic environments	-	-
IEC 61000-3-2	- ¹⁾	Electromagnetic compatibility (EMC) - Part 3-2: Limits - Limits for harmonic current emissions (equipment input current ≤ 16 A per phase)	EN 61000-3-2	2006 ²⁾
IEC 61000-3-3	- ¹⁾	Electromagnetic compatibility (EMC) - Part 3-3: Limits - Limitation of voltage changes, voltage fluctuations and flicker in public low-voltage supply systems, for equipment with rated current ≤ 16 A per phase and not subject to conditional connection	EN 61000-3-3 + corr. July	1995 ²⁾ 1997
IEC/TS 61000-3-4	- ¹⁾	Electromagnetic compatibility (EMC) - Part 3-4: Limits - Limitation of emission of harmonic currents in low-voltage power supply systems for equipment with rated current greater than 16 A	-	-
IEC/TS 61000-3-5 (mod)	- ¹⁾	Electromagnetic compatibility (EMC) - Part 3: Limits - Section 5: Limitation of voltage fluctuations and flicker in low-voltage power supply systems for equipment with rated current greater than 16 A	-	-
IEC 61000-3-6	- ¹⁾	Electromagnetic compatibility (EMC) - Part 3: Limits - Section 6: Assessment of emission limits for distorting loads in MV and HV power systems	-	-

¹⁾ Undated reference.

²⁾ Valid edition at date of issue.

<u>Publication</u>	<u>Year</u>	<u>Title</u>	<u>EN/HD</u>	<u>Year</u>
IEC 61000-3-11	- ¹⁾	Electromagnetic compatibility (EMC) - Part 3-11: Limits - Limitation of voltage changes, voltage fluctuations and flicker in public low-voltage supply systems - Equipment with rated current ≤ 75 A and subject to conditional connection	EN 61000-3-11	2000 ²⁾
IEC 61000-3-12	- ¹⁾	Electromagnetic compatibility (EMC) - Part 3-12: Limits - Limits for harmonic currents produced by equipment connected to public low-voltage systems with input current > 16 A and ≤ 100 A per phase	EN 61000-3-12	2005 ²⁾
IEC 61000-4-2	- ¹⁾	Electromagnetic compatibility (EMC) - Part 4-2: Testing and measurement techniques - Electrostatic discharge immunity test	EN 61000-4-2	1995 ²⁾
IEC 61000-4-3	- ¹⁾	Electromagnetic compatibility (EMC) - Part 4-3: Testing and measurement techniques - Radiated, radio-frequency, electromagnetic field immunity test	EN 61000-4-3	2006 ²⁾
IEC 61000-4-4	- ¹⁾	Electromagnetic compatibility (EMC) - Part 4-4: Testing and measurement techniques - Electrical fast transient/burst immunity test	EN 61000-4-4	2004 ²⁾
IEC 61000-4-5	- ¹⁾	Electromagnetic compatibility (EMC) - Part 4-5: Testing and measurement techniques - Surge immunity test	EN 61000-4-5	2006 ²⁾
IEC 61000-4-6	- ¹⁾	Electromagnetic compatibility (EMC) - Part 4-6: Testing and measurement techniques - Immunity to conducted disturbances, induced by radio-frequency fields	-	-
IEC 61000-4-7	- ¹⁾	Electromagnetic compatibility (EMC) - Part 4-7: Testing and measurement techniques - General guide on harmonics and interharmonics measurements and instrumentation, for power supply systems and equipment connected thereto	EN 61000-4-7	2002 ²⁾
IEC 61000-4-8	- ¹⁾	Electromagnetic compatibility (EMC) - Part 4-8: Testing and measurement techniques - Power frequency magnetic field immunity test	EN 61000-4-8	1993 ²⁾
IEC 61000-4-9	- ¹⁾	Electromagnetic compatibility (EMC) - Part 4-9: Testing and measurement techniques - Pulse magnetic field immunity test	EN 61000-4-9	1993 ²⁾
IEC 61000-4-10	- ¹⁾	Electromagnetic compatibility (EMC) - Part 4-10: Testing and measurement techniques - Damped oscillatory magnetic field immunity test	EN 61000-4-10	1993 ²⁾

<http://www.china-gauges.com/>

<u>Publication</u>	<u>Year</u>	<u>Title</u>	<u>EN/HD</u>	<u>Year</u>
IEC 61000-4-11	- ¹⁾	Electromagnetic compatibility (EMC) - Part 4-11: Testing and measurement techniques - Voltage dips, short interruptions and voltage variations immunity tests	EN 61000-4-11	2004 ²⁾
IEC 61000-4-12	- ¹⁾	Electromagnetic compatibility (EMC) - Part 4-12: Testing and measurement techniques - Ring wave immunity test	EN 61000-4-12	2006 ²⁾
IEC 61000-4-13	- ¹⁾	Electromagnetic compatibility (EMC) - Part 4-13: Testing and measurement techniques - Harmonics and interharmonics including mains signalling at a.c. power port, low frequency immunity tests	EN 61000-4-13	2002 ²⁾
IEC 61000-4-14	- ¹⁾	Electromagnetic compatibility (EMC) - Part 4-14: Testing and measurement techniques - Voltage fluctuation immunity test	EN 61000-4-14	1999 ²⁾
IEC 61000-4-15	- ¹⁾	Electromagnetic compatibility (EMC) - Part 4-15: Testing and measurement techniques - Flickermeter - Functional and design specifications	EN 61000-4-15	1998 ²⁾
IEC 61000-4-16	- ¹⁾	Electromagnetic compatibility (EMC) - Part 4-16: Testing and measurement techniques - Test for immunity to conducted, common mode disturbances in the frequency range 0 Hz to 150 kHz	EN 61000-4-16	1998 ²⁾
IEC 61000-4-17	- ¹⁾	Electromagnetic compatibility (EMC) - Part 4-17: Testing and measurement techniques - Ripple on d.c. input power port immunity test	EN 61000-4-17	1999 ²⁾
IEC 61000-4-18	- ¹⁾	Electromagnetic compatibility (EMC) - Part 4-18: Testing and measurement techniques - Oscillatory wave immunity test	-	-
IEC 61000-4-20	- ¹⁾	Electromagnetic compatibility (EMC) - Part 4-20: Testing and measurement techniques - Emission and immunity testing in transverse electromagnetic (TEM) waveguides	EN 61000-4-20	2003 ²⁾
IEC 61000-4-21	- ¹⁾	Electromagnetic compatibility (EMC) - Part 4-21: Testing and measurement techniques - Reverberation chamber test methods	EN 61000-4-21	2003 ²⁾
IEC 61000-4-23	- ¹⁾	Electromagnetic compatibility (EMC) - Part 4-23: Testing and measurement techniques - Test methods for protective devices for HEMP and other radiated disturbances	EN 61000-4-23	2000 ²⁾
IEC 61000-4-24	- ¹⁾	Electromagnetic compatibility (EMC) - Part 4: Testing and measurement techniques - Section 24: Test methods for protective devices for HEMP conducted disturbance	EN 61000-4-24	1997 ²⁾

<u>Publication</u>	<u>Year</u>	<u>Title</u>	<u>EN/HD</u>	<u>Year</u>
IEC 61000-4-25	- ¹⁾	Electromagnetic compatibility (EMC) - Part 4-25: Testing and measurement techniques - HEMP immunity test methods for equipment and systems	EN 61000-4-25	2002 ²⁾
IEC 61000-4-27	- ¹⁾	Electromagnetic compatibility (EMC) - Part 4-27: Testing and measurement techniques - Unbalance, immunity test	EN 61000-4-27	2000 ²⁾
IEC 61000-4-28	- ¹⁾	Electromagnetic compatibility (EMC) - Part 4-28: Testing and measurement techniques - Variation of power frequency, immunity test	EN 61000-4-28	2000 ²⁾
IEC 61000-4-29	- ¹⁾	Electromagnetic compatibility (EMC) - Part 4-29: Testing and measurement techniques - Voltage dips, short interruptions and voltage variations on d.c. input power port immunity tests	EN 61000-4-29	2000 ²⁾
IEC 61000-4-30	- ¹⁾	Electromagnetic compatibility (EMC) - Part 4-30: Testing and measurement techniques - Power quality measurement methods	EN 61000-4-30	2003 ²⁾
IEC/TR 61000-4-32	- ¹⁾	Electromagnetic compatibility (EMC) - Part 4-32: Testing and measurement techniques - High-altitude electromagnetic pulse (HEMP) simulator compendium	-	-
IEC 61000-4-33	- ¹⁾	Electromagnetic compatibility (EMC) - Part 4-33: Testing and measurement techniques - Measurement methods for high-power transient parameters	-	-
IEC 61000-4-34	- ¹⁾	Electromagnetic compatibility (EMC) - Part 4-34: Testing and measurement techniques - Voltage dips, short interruptions and voltage variations immunity tests for equipment with input current more than 16 A per phase	-	-

<http://www.china-gauges.com/>

BSI — British Standards Institution

BSI is the independent national body responsible for preparing British Standards. It presents the UK view on standards in Europe and at the international level. It is incorporated by Royal Charter.

Revisions

British Standards are updated by amendment or revision. Users of British Standards should make sure that they possess the latest amendments or editions.

It is the constant aim of BSI to improve the quality of our products and services. We would be grateful if anyone finding an inaccuracy or ambiguity while using this British Standard would inform the Secretary of the technical committee responsible, the identity of which can be found on the inside front cover. Tel: +44 (0)20 8996 9000. Fax: +44 (0)20 8996 7400.

BSI offers members an individual updating service called PLUS which ensures that subscribers automatically receive the latest editions of standards.

Buying standards

Orders for all BSI, international and foreign standards publications should be addressed to Customer Services. Tel: +44 (0)20 8996 9001. Fax: +44 (0)20 8996 7001. Email: orders@bsi-global.com. Standards are also available from the BSI website at <http://www.bsi-global.com>.

In response to orders for international standards, it is BSI policy to supply the BSI implementation of those that have been published as British Standards, unless otherwise requested.

Information on standards

BSI provides a wide range of information on national, European and international standards through its Library and its Technical Help to Exporters Service. Various BSI electronic information services are also available which give details on all its products and services. Contact the Information Centre. Tel: +44 (0)20 8996 7111. Fax: +44 (0)20 8996 7048. Email: info@bsi-global.com.

Subscribing members of BSI are kept up to date with standards developments and receive substantial discounts on the purchase price of standards. For details of these and other benefits contact Membership Administration. Tel: +44 (0)20 8996 7002. Fax: +44 (0)20 8996 7001. Email: membership@bsi-global.com.

Information regarding online access to British Standards via British Standards Online can be found at <http://www.bsi-global.com/bsonline>.

Further information about BSI is available on the BSI website at <http://www.bsi-global.com>.

Copyright

Copyright subsists in all BSI publications. BSI also holds the copyright, in the UK, of the publications of the international standardization bodies. Except as permitted under the Copyright, Designs and Patents Act 1988 no extract may be reproduced, stored in a retrieval system or transmitted in any form or by any means – electronic, photocopying, recording or otherwise – without prior written permission from BSI.

This does not preclude the free use, in the course of implementing the standard, of necessary details such as symbols, and size, type or grade designations. If these details are to be used for any other purpose than implementation then the prior written permission of BSI must be obtained.

Details and advice can be obtained from the Copyright & Licensing Manager. Tel: +44 (0)20 8996 7070. Fax: +44 (0)20 8996 7553. Email: copyright@bsi-global.com.